

Generador Trifasico (SG106/S3)

<i>Potencia Stand By</i>	KW/KVA	85 / 106
<i>Potencia Prime</i>	KW/KVA	77 / 96
<i>Frecuencia Nominal</i>	Hz	50
<i>Tension Nominal Sistema</i>	V	12 / 24
<i>Voltaje Disponible</i>	V	380/220 – 400/230
<i>Factor de Potencia</i>	%	0,8
<i>Capacidad Combustible</i>	Lt	810
<i>Peso</i>	Kg	1900
<i>Abierto / Cerrado</i>		Cerrado
<i>Dimensiones</i>	mm	3170 x 1100 x 1780



<i>Consumo de Combustible</i>	<i>1500 Rpm</i>
<i>Potencia Stand By</i>	25 [Lts/hrs]
<i>Potencia Prime</i>	22 [Lts/hrs]
<i>Potencia Prime (75%)</i>	17 [Lts/hrs]
<i>Potencia Prime (50%)</i>	11 [Lts/hrs]

Talca
Av. San Miguel 3380
Tel: +569 68999342

Curicó
Av. Alessandri 2008
Tel: +569 68999339