

## Generador Trifasico (C180D5)

<i>Potencia Stand By</i>	KW/KVA	144 / 180
<i>Potencia Prime</i>	KW/KVA	131 / 164
<i>Frecuencia Nominal</i>	Hz	50
<i>Tension Nominal Sistema</i>	V	12
<i>Voltaje Disponible</i>	V	380/220V – 400/230V
<i>Factor de Potencia</i>	%	0,8
<i>Capacidad Combustible</i>	Lt	360
<i>Peso</i>	Kg	2973
<i>Abierto / Cerrado</i>		Cerrado
<i>Dimensiones</i>	mm	3890 x 1360 x 2300



<i>Consumo de Combustible</i>	<i>1500 Rpm</i>
<i>Potencia Stand By</i>	40,0 [Lts/hrs]
<i>Potencia Prime</i>	36,0 [Lts/hrs]
<i>Potencia Prime (75%)</i>	27,0 [Lts/hrs]
<i>Potencia Prime (50%)</i>	19,0 [Lts/hrs]

**Talca**  
Av. San Miguel 3380  
Tel: +569 68999342

**Curicó**  
Av. Alessandri 2008  
Tel: +569 68999339